



GTEN Infinite v5 Series

LTE Modem Router

Changing APN Setting

Please follow the Infinite Tablet Modem/Router login steps below:

1. Connect to the Network (2.4G, or 5G SSID) with the router (Default SSID is displayed on the sticker at the bottom of the router).
2. Enter the default Wifi password (The default WIFI password [WIFI key] is displayed on the sticker at the bottom of the router).
3. Make sure you are connected to the correct network (SSID), then open a web browser, e.g., Google Chrome, Firefox, Safari, Edge, or Explorer.
4. In the URL address bar (web address), type in 192.168.2.1, and press “Enter”, or “Return”, on your keyboard. ***It is not necessary to enter “http://”**
5. You should be at the login page for the router settings. The default **username** and **password** for the router settings login is (in all lower case, for both): **admin**
6. At the router’s main page, on the left, under **Advanced Settings**, click the **4G Modem Setting** link.
7. Find **ISP**, then select from the drop down menu the appropriate APN settings for your internet service plan. ***please contact Tech support for your plan’s correct APN settings, or refer to Appendix A**
 - a. If no option is available from the drop down menu, select **Other**, then enter the required information in the **APN Service**, **PDP Type**, and **Authentication** fields.
8. Once the correct APN is completed (if the drop down menu has been selected, the remaining required fields will auto-populate... or entered manually), at the bottom of the page click **Apply** to save the settings.
9. Finally, in the upper right section of the page, click the **Reboot** icon:  **4.3.9-202101**
 - a. The modem/router will power cycle and restart. Please wait 5-10 minutes for the device to complete reboot. Log into the router settings and confirm the APN settings have been saved (Following steps 1-7).

